

EHF-FD1513





Panasonic

POWER DIVIDER 1720-1790MHZ

Contains lead / RoHS non-compliant

RF/IF and RFID

 [EHF-FD1513.pdf](#)

 Buy Now

We can supply Panasonic EHF-FD1513, use the request quote form to request EHF-FD1513 pirce, Panasonic Datasheet PDF and lead time.Zeanoit.com is a professional electronic components distributor. With 3+ Million line items of available electronic components can ship in short lead-time, over 250 thousand part numbers of electronic components in stock for immediately delivery, which may include part number EHF-FD1513.The price and lead time for EHF-FD1513 depending on the quantity required, availability and warehouse location.

Shopping Process

- 1

Confirm the product
- >
- 2

submit the order
- >
- 3

payment
- >
- 4

wait for delivery
- >
- 5

receive the goods

Specifications

Specifications:	-
Size / Dimension:	0.126" L x 0.063" W (3.20mm x 1.60mm)
Series:	-
Packaging:	Bulk
Package / Case:	-
Insertion Loss:	4dB
Frequency:	1720 ~ 1790MHz Operating

Related products



**EHF-FD1506**  
POWER DIVIDER 1607-1685MHZ  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1509**  
POWER DIVIDER 2100-2200MHZ  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1540**  
DIRECTIONAL COUPLER 800MHZ 17DB  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1542**  
COUPLER DIRECTIONAL 1900 MHZ  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1508**  
POWER DIVIDER 1000-1050MHZ  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1545**  
POWER SPLITTER 650-2000MHZ  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1503**  
POWER DIVIDER 1546-1630MHZ  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1541**  
DIRECTIONAL COUPLER 1850MHZ-14DB  
[Panasonic Electronic Components](#)

RFQ



**EHF-FD1546**  
DIRECTIONAL COUPLER 800 MHZ 17DB  
[Panasonic Electronic Components](#)


RFQ



**EHF-FD1507**  
POWER DIVIDER 1880-1920MHZ  
[Panasonic Electronic Components](#)


RFQ

Guess You May Looking For




**RT1210WRD0741R2L**  
RES SMD 41.2 OHM 0.05% 1/4W 1210  
[Yageo](#)

RFQ




**RT1210WRD07432RL**  
RES SMD 432 OHM 0.05% 1/4W 1210  
[Yageo](#)

RFQ




**RG1608V-2321-W-T1**  
RES SMD 2.32K OHM 1/10W 0603  
[Susumu](#)

RFQ




**RT1210WRD072K7L**  
RES SMD 2.7K OHM 0.05% 1/4W 1210  
[Yageo](#)

RFQ




**RT1206WRC0730R1L**  
RES SMD 30.1 OHM 0.05% 1/4W 1206  
[Yageo](#)

RFQ




**RT1206WRC07130RL**  
RES SMD 130 OHM 0.05% 1/4W 1206  
[Yageo](#)

RFQ




**RT1206WRC07274RL**  
RES SMD 274 OHM 0.05% 1/4W 1206  
[Yageo](#)

RFQ




**RT1206WRC0726K7L**  
RES SMD 26.7KOHM 0.05% 1/4W 1206  
[Yageo](#)

RFQ



**RT1206WRC0716R5L**  
RES SMD 16.5 OHM 0.05% 1/4W 1206  
[Yageo](#)

RFQ



**RG1005V-4640-W-T1**  
RES SMD 464 OHM 0.05% 1/16W 0402  
[Susumu](#)

RFQ