

EHF-FD1624



Panasonic

BALUN HYBRID 3400-4000MHZ 1:4
Contains lead / RoHS non-compliant
RF/IF and RFID

[EHF-FD1624.pdf](#)

Buy Now

We can supply Panasonic EHF-FD1624, use the request quote form to request EHF-FD1624 price, Panasonic Datasheet PDF and lead time. Zeano.com is a professional electronic components distributor. With 3+ Million line items of available electronic components can ship in short lead-time, over 250 thousand part numbers of electronic components in stock for immediately delivery, which may include part number EHF-FD1624. The price and lead time for EHF-FD1624 depending on the quantity required, availability and warehouse location.

Shopping Process

1

Confirm the product

2

submit the order

3

payment

4

wait for delivery

5

receive the goods

Specifications

Series:	EHF
Return Loss (Min):	-
Phase Difference:	180° ±15
Packaging:	Bulk
Package / Case:	0606 (1616 Metric), Concave
Mounting Type:	Surface Mount
Insertion Loss (Max):	2.0dB
Impedance - Unbalanced/Balanced:	50 / 200 Ohm
Frequency Range:	3.4GHz ~ 4GHz

Related products

Panasonic

EHF-FD1624B
BALUN HYBRID 1600-1950 MHZ 1:4
[Panasonic Electronic Components](#)

RFQ



EHF-FD1622
BALUN HYBRID 750-950MHZ 1:4
[Panasonic Electronic Components](#)

RFQ

Panasonic

EHF-FD1722
DIRECT COUPLER W/LC 880MHZ 16DB
[Panasonic Electronic Components](#)

RFQ

Panasonic

EHF-FD1631
BALUN DUAL 1800-2000 MHZ 1:1
[Panasonic Electronic Components](#)

RFQ

Panasonic

EHF-FD1618
BALUN HYBRID 700-1300MHZ 1:1
[Panasonic Electronic Components](#)

RFQ

Panasonic

EHF-FD1621
BALUN HYBRID 1100-1450MHZ 1:4
[Panasonic Electronic Components](#)

RFQ



EHF-FD1626
BALUN HYBRID 1700-1900MHZ 1:4
[Panasonic Electronic Components](#)

RFQ

Panasonic

EHF-FD1619
BALUN HYBRID 1200-2200MHZ 1:1
[Panasonic Electronic Components](#)

RFQ



EHF-FD1620
BALUN HYBRID 950-1250 MHZ 1:4
[Panasonic Electronic Components](#)

RFQ

Panasonic

EHF-FD1629
BALUN 1700-2000 MHZ 50/50 OHM
[Panasonic Electronic Components](#)

RFQ

Guess You May Looking For




RG3216N-6342-D-T5
RES SMD 63.4K OHM 0.5% 1/4W 1206
[Susumu](#)

RFQ




RNCF2010BTE15K4
RES SMD 15.4K OHM 0.1% 1/3W 2010
[Stackpole Electronics Inc.](#)

RFQ




CPF1206B3K9E1
RES SMD 3.9K OHM 0.1% 1/8W 1206
[TE Connectivity Passive Product](#)

RFQ




RCWE121082L5FKEA
RES SMD 0.0825 OHM 1% 1W 1210
[Vishay Dale](#)

RFQ



CPF1206B2K94E1
RES SMD 2.94K OHM 0.1% 1/8W 1206
[TE Connectivity Passive Product](#)

RFQ




CPF1206B357RE1
RES SMD 357 OHM 0.1% 1/8W 1206
[TE Connectivity Passive Product](#)

RFQ




RNCF1210BTE21R5
RES SMD 21.5 OHM 0.1% 1/3W 1210
[Stackpole Electronics Inc.](#)

RFQ



CPF1206B240RE1
RES SMD 240 OHM 0.1% 1/8W 1206
[TE Connectivity Passive Product](#)

RFQ



CPF1206B825RE1
RES SMD 825 OHM 0.1% 1/8W 1206
[TE Connectivity Passive Product](#)

RFQ



RNCF1210BTE31K6
RES SMD 31.6K OHM 0.1% 1/3W 1210
[Stackpole Electronics Inc.](#)

RFQ